

In the Claims:

Rewrite claims 1 and 2 as follows:

1. (Currently amended) Device for detecting electromagnetic radiations, and in particular infrared radiations, implementing a detection circuit associated with a reading circuit, the detection circuit ~~comprising~~ consisting of an array of detection pixels (1), each of ~~the~~ said pixels ~~consisting of~~ comprising a thermal detector of biased ~~(3)~~ bolometric type (2), and delivering an electric current signal representative of ~~the~~ detected radiation, ~~the~~ said current signal undergoing a double baselining, respectively:

- a global baselining carried out by means of a thermally isolated bolometer (8), ensuring ~~the~~ extraction from ~~the~~ said electric current signal, of a first current of constant value inherent to ~~the~~ biasing of the said thermal detector (2),
- an adaptive baselining specific to each of the pixels (1), carried out by means of a programmable current generator (9), specific to each of the pixels, generating a current for subtraction from ~~the~~ said signal, as a function of ~~the~~ dispersion inherent to the pixel considered relative to a reference signal and stored in an associated memory,

~~characterized in that the~~ wherein said associated memory is integrated at ~~the~~ a level of each of ~~the~~ said pixels.

2. (Currently amended) Device for detecting electromagnetic radiations according to Claim 1, ~~characterized in that the~~ wherein a phase of reading ~~the~~ data of each of ~~the~~ memories associated with ~~the~~ said pixels occurs between ~~the~~ an end of ~~the~~ integration of a row n and ~~the~~ start of ~~the~~ integration of a row n+1 of the array of ~~the~~ said pixels.